DESCRIPTION

The DRS1AF~DRS1MF are available in SMAF package

ORDERING INFORMATION

| Package Type | Part Number | | | | |
|--|--------------------|--------|--|--|--------|
| | DRS1AF | | | | |
| | DRS1BF | | | | |
| SMAF | DRS1DF | | | | |
| | DRS1GF DRS1JF | | | | |
| | | | | | DRS1KF |
| | | DRS1MF | | | |
| Note | SPQ: 3,000pcs/Reel | | | | |
| AiT provides all RoHS Compliant Products | | | | | |

PIN DESCRIPTION



FEATURES

- For surface mounted applications
- Low profile package
- Glass Passivated Chip Junction
- Easy to pick and place
- Fast reverse recovery time
- Available in SMAF package

MECHANICAL DATA

Case: SMAF

Terminals: Solderable per MIL-STD-750,

Method 2026

Approx. Weight: 27mg 0.00086oz

DRS1AF~DRS1MF

FAST RECOVERY RECTIFIER DIODE REVERSE VOLTAGE 50V TO 1000V FORWARD CURRENT 1A

MAXIMUM RATINGS AND ELECTRICAL CHARACTERISTICS

Ratings at 25°C ambient temperature unless otherwise specified. Single phase half-wave 60 Hz, resistive or inductive load, for capacitive load current derate by 20 %.

| Parameter | | Symbol | DRS1AF | DRS1BF | DRS1DF | DRS1GF | DRS1JF | DRS1KF | DRS1MF | Unit |
|--|---|--------------------|-------------|--------|--------|--------|--------|--------|--------|------|
| Maximum Repetitive Peak Reverse Voltage | | V_{RRM} | 50 | 100 | 200 | 400 | 600 | 800 | 1000 | V |
| Maximum RMS Volta | Maximum RMS Voltage | | 35 | 70 | 140 | 280 | 420 | 560 | 700 | V |
| Maximum DC Blockir | ng Voltage | V _{DC} | 50 | 100 | 200 | 400 | 600 | 800 | 1000 | V |
| Maximum Average Forward Rectified Current at T _A =65°C | | I _{F(AV)} | 1.0 | | | | | | Α | |
| Peak Forward Surge Current 8.3ms Single Half Sine Wave Superimposed on Rated Load (JEDEC Method) | | I _{FSM} | 25 | | | | | | Α | |
| Maximum Instantaneous Forward Voltage at 1A | | V _F | | 1.3 | | | | | | V |
| Maximum DC Reverse Current at Rated DC Blocking Voltage | T _A =25°C T _A =125°C | I _R | 5.0 100 | | | | | μΑ | | |
| Maximum Reverse Recovery TimeNOTE1 | | t _{rr} | 150 250 500 | | | | | 00 | ns | |
| Typical Junction Capacitance ^{NOTE2} | | Сл | 15 | | | | | | рF | |
| Operating and Storage Temperature Range | | TJ, Tstg | -55 ~150 | | | | | | °C | |

NOTE1: Measured with I_F =0.5A, I_R =1A, I_{rr} =0.25A

NOTE2: Measured at 1MHz and applied reverse voltage of 4V D.C

TYPICAL CHARACTERISTICS

Figure. 1 Forward Current Derating Curve




Figure. 3 Typical Instantaneous Forward




Figure. 5 Maximum Non-Repetitive Peak Forward




Figure. 2 Typical Reverse Characteristics





Figure. 4 Typical Junction Capacitance




Bottom View

PACKAGE INFORMATION


Dimension in SMAF (Unit: mm)

Plastic surface mounted package; 2 leads



The recommended mounting pad size

Top View



| UN | VIT | Α | С | D | Е | е | g | HE | 4 | |
|-----|-----|-----|------|-----|-----|-----|-----|-----|------------|--|
| mm | Max | 1.1 | 0.20 | 3.7 | 2.7 | 1.6 | 1.2 | 4.9 | | |
| | Min | 0.9 | 0.12 | 3.3 | 2.4 | 1.3 | 0.8 | 4.4 | 7 ° | |
| mil | Max | 43 | 7.9 | 146 | 106 | 63 | 47 | 193 | / | |
| | Min | 35 | 4.7 | 130 | 94 | 51 | 31 | 173 | | |

DRS1AF~DRS1MF

FAST RECOVERY RECTIFIER DIODE

REVERSE VOLTAGE 50V TO 1000V FORWARD CURRENT 1A

IMPORTANT NOTICE

AiT Semiconductor Inc. (AiT) reserves the right to make changes to any its product, specifications, to discontinue any integrated circuit product or service without notice, and advises its customers to obtain the latest version of relevant information to verify, before placing orders, that the information being relied on is current.

AiT Semiconductor Inc.'s integrated circuit products are not designed, intended, authorized, or warranted to be suitable for use in life support applications, devices or systems or other critical applications. Use of AiT products in such applications is understood to be fully at the risk of the customer. As used herein may involve potential risks of death, personal injury, or servere property, or environmental damage. In order to minimize risks associated with the customer's applications, the customer should provide adequate design and operating safeguards.

AiT Semiconductor Inc. assumes to no liability to customer product design or application support. AiT warrants the performance of its products of the specifications applicable at the time of sale.